



Please scan the QR code or visit the link to access the page where you can **register as a dealer, login to Aryo Cloud, or access the Dealer Resource Center** to download the product manual for more detailed information.

Do not power up Surf prior to user and device registration. Always do the wiring and panel programming prior to Surf power up.

1) Add User & Device on Aryo Cloud

- Input user information
- Input device information
- Input panel information
- Add and label partitions & zones

2) Connect to Alarm Panel

- Make the necessary wiring connections between Surf and alarm panel
- Power up panel and Surf
- Surf will report the panel connection settings to Aryo Cloud

Cable Color Code	
Red	DC +
Black	DC -
Blue	Zone
Brown	PGM
Yellow	Ring
Green	Tip

3) Alarm Panel Programming

- **Line Capture (Tip/ Ring):**
 - Surf will capture all CID/SIA signals
 - PGM and zone are used for keyswitch arming
 - Program your panel for digital monitoring

4) Set-up User Mobile App

- After registration, user will receive an email from Aryo Cloud with a link to set up their account
- User downloads Aryo App from the App Store (iOS) or Google Play (Android)
- After user successfully logs in to Aryo App, they will be prompted to change their password
- Once the new password is set, user is now able to use the app to access their system
- User creates Surf master code

7) LEDs

Condition	Status	LED	Color	On	Off	Fast blink	1 blink	2 blinks	3 blinks	On-1 blink	On-2 blinks
Power	DC power on	1	Red	X							
	DC power off	1	Red		X						
	Device not registered	1	Red				X				
	Device troubles	1	Red			X					
	Firmware update in progress	1&2	Red/Green	Alternating. LED 1 is on/off while LED 2 is off/on.							
Cellular Network	Can not find the cellular network	2	Green			X					
	Poor cellular signal	2	Green				X				
	Medium cellular signal	2	Green					X			
	Good cellular signal	2	Green						X		
Server Network	Connected to server & good signal	2	Green	X							
	Communicating with server	2	Green			X					
	Connected to network & poor cellular signal	2	Green							X	
	Connected to network & medium cellular signal	2	Green								X